KB12180 12V 17Ah



The KB Standard series consists in VRLA batteries - AGM technology (Absorbent Glass Mat), with a design life of 3-5 years and it is designed for general applications such as UPS, telecommunications and electrical applications.




Performance Characteristics


Nominal Voltage	12V				
Dimensions	Length (mm / inch)	181 / 7.13			
	Width (mm / inch)	77 / 3.03			
	Height (mm / inch)	167 / 6.57			
	Total Height (mm / inch)	167 / 6.57			
Approx Weight	(Kg / lbs)	5.3 / 11.7			
Design Life	5 years				
Terminal	M5				
Container Material	ABS				
Rated Capacity	17.0Ah / 0.85A	(20hr, 10.5V / cell, 25ºC / 77ºF)			
	16.8Ah / 1.68A	(10hr, 10.5V / cell, 25ºC / 77ºF)			
	15.45Ah / 3.09A	(5hr, 10.5V / cell, 25ºC / 77ºF)			
	11.8h / 11.8A	(1hr, 9.6V / cell, 25ºC / 77ºF)			
Max. Discharge Current	255A (5s)				
Internal Resistance	Approx 16.5m Ω				
Operating Temp. Range	Discharge : -20 ~ 60°C (-4 ~140°F)				
	Charge : -10 ~ 60°C (14 ~ 140°F)				
	Storage : -20 ~ 60°C (-4 ~ 140°F)				
Nominal Operating Temp. Range	25 ± 3°C (77 ± 5°F)				
Cycle Use	Initial Charging Current less than 6.8A				
	Voltage: 14.5V ~ 14.9V at 25°C (77°F)				
	Temp. Coefficient: -20mV/ºC				
Standby Use	No limit on Initial Chargi	ng Current			
	Voltage: 13.6V ~ 13.8V at 25°C (77°F)				
	Temp. Coefficient: -20mV/				
Capacity affected by Temperature	40°C (104°F)	103%			
	25ºC (77ºF)	100%			
	0°C (32°F)	86%			
Self Discharge	Fully charged Kaise Standard Series batteries may be				
	stored for up to 6 months at 25°C (77°F) and then a				
	freshening charge is required. For higher temperatures the				
	time interval will be shor	rter.			

Discharge Constant Current (Amperes) at 77°F (25°C)

Volts/cell	5min	10min	15min	30min	1h	3h	5h	10h	20h
1.80V	55.3	39.4	30.9	17.9	10.9	4.27	2.84	1.65	0.84
1.75V	58	40.7	31.8	18.4	11.2	4.35	2.90	1.68	0.85
1.70V	60.5	41.9	32.6	18.9	11.4	4.42	2.97	1.72	0.87
1.65V	62.8	43	33.3	19.4	11.6	4.5	3.03	1.75	0.88
1.60V	64.9	44.1	34	19.8	11.8	4.57	3.09	1.78	0.89

Dimensions and Terminal (Unit: mm (inches))





Applications

Alarm systems
Cable television
Communications Equipment
Control Equipment
Computers
Electronic Cash Registers
Electric Test Equipment
Emergency lighting systems
Fire & Security
Geophysical equipment

Marine equipment Medical equipment Micro processor based office machines Portable cine & Video lights Solar powered systems Telecommunications systems Television & Video recorders Toys Uninterruptible power supply systems Vending machines

Certifications

ISO 9001:2008 ISO 14001:2008



Discharge Current vs. Discharge Voltage

Final discharge voltage V/CELL	1.8	1,75	1,7	1,6
Discharge current	≤ 0,1CA	0.25 CA \geq I > 0.1 CA	$0.55\text{CA} \ge I > 0.25\text{CA}$	> 0.55CA


Discharge Constant Power (Watts per cell) at 77°F (25°C)

Volts/cell	5min	10min	15min	30min	45min	1h	2h	3h	5h
1.80V	94.0	72.8	56.5	33.1	26.0	21.5	12.5	8.74	5.88
1.75V	98.0	74.3	57.8	33.7	26.4	21.7	12.7	8.83	5.95
1.70V	103	75.8	59.0	34.3	26.8	22.0	12.8	8.92	6.01
1.65V	107	77.2	60.2	34.8	27.1	22.2	12.9	9.01	6.07
1.60V	111	78.6	61.3	35.3	27.4	22.4	13.0	9.09	6.13


(Note) The above characteristics data are average values obtained within three charge/discharge cycles not the mimimum values.




Charging Characteristics (float use)



Temperature Effects in Relation to Battery Capacity




Self Discharge Characteristics




IMPORTANT NOTE: The specifications presented herein are subject to revision without notice.

Cycle Life in Relation to Depth of Discharge



Effect of Temperature on Long Term Float Life





No supplementary charge required (carrry out supplementary charge before use if 100% capacity is required)

Supplementary charge required before use. Optional charging way a below: 1. Charged for above 3 days at limited current 0.25 CA and constant voltage 2.25V / cell. 2. Charged fo above 20 hours limited current 0.25CA and constant voltage 2.45V / cell. 3. Charged for 8-10 hours ar limited current 0.05 CA.

Supplementary charge often fail to recover the capacity. The battery should never be left standing till this is reached.

energy@tempelgroup.com www.tempelgroup.com

Tempel Group en el mundo

BARCELONA • MADRID • VALENCIA • BILBAO • SEVILLA • LISBOA • PORTO • BUENOS AIRES • LIMA SANTIAGO DE CHILE • BOGOTÁ • SÃO PAULO • CIUDAD DE MÉXICO • CIUDAD DE PANAMÁ • MONTEVIDEO • QUITO



